


PART NUMBERING



ALUMINUM ELECTROLYTIC CAPACITORS

Product symbol system for Aluminum Electrolytic Capacitors.



Type	Code
CDVS	VS
CDVB	VB
CDVH	VH
CDVZ	VZ
CD11CX	SA
CD50BP	SB
CD71C	SC
CD11CH	SD
CD50S	SE
CD50H	SF
CD50Z	SG
CD113	RA
CD113H	RB
CD117	RC
CD117H	RD
CD110	RF
CD110X	RF
CD110XC	RG
CD11H	RH
CD11A	RI
CD268	PA
CD265	PB
CD269	PC
CD26L	PD
CD26J	PE
CD26H	PF
CD267	PG
CD264	PH
CD266	PI
CD261	PJ
CD288	KB
CD288H	KC
CD288HL	KD
CDME	KE
CD71	WA
CD72	WB
CD71H	WC
CDSH	WD
CD72H	WE
CDS	WS
CD17S	FS
CD17FX	FX
CD95	AA
CD95B	AB
CD292	LC
CD293	LD
CD294	LE
CD295	LF
CD296	LG
CD297	LH
CD298	LI
CD92	GA
CD92H	GB
CD13N	GC
CD92L	GD
CD13NH	GE
CD13L	GF
CD13HL	GG
CD98SK	GK
CD60	GM
CDIN	IN

Voltage	Code
4	0G
6.3	0J
10	1A
16	1C
20	1D
25	1E
35	1V
40	1G
50	1H
63	1J
80	1K
100	2A
120	2B
160	2C
180	2K
200	2D
250	2E
315	2F
330	2T
350	2V
360	2X
400	2G
420	2N
450	2W
500	2H
550	2Y

Cap(µF)	Code
0.1	0R1
0.22	R22
0.33	R33
0.47	R47
0.68	R68
1	010
2.2	2R2
3.3	3R3
4.7	4R7
6.8	6R8
10	100
22	220
33	330
47	470
68	680
100	101
120	121
150	151
180	181
220	221
330	331
470	471
680	681
1000	102
1200	122
2200	222
2700	272
3300	332
4700	472
10000	103
22000	223
33000	333
47000	473
68000	683
100000	104
220000	224
330000	334
470000	474
680000	684
1000000	105
1500000	155

Tolerance (%)	Code
+5	J
-5	J
+10	K
-10	K
+15	L
-15	L
+20	M
-20	M
+30	F
0	F
+30	Q
-10	Q
+20	R
0	R
+50	T
-10	T
+75	U
-10	U
+20	V
-10	V
+30	N
-30	N
+50	S
-20	S

Lead cut and forming	Code
Taping	TB
	FC
	FM
	CC
	MC

Lead Space	Code
2.0	F20
2.5	F25
3.5	F35
5.0	F50
7.5	F75
10	F100

For example: CD110X 50V 10UF 20% Taping F2.0 5X11

R	F	I	H	1	0	0	M	T	B	F	2	0	0	0	5	0	1	1
---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---